



## ENAIKOON radio-switch-pro

### Transmitter-Receiver Set for Wireless Control of an ENAIKOON Remote Surveillance Module

The ENAIKOON radio-switch-pro is typically used for the following reasons:

- activate/de-activate an ENAIKOON remote surveillance module
- set off an alarm

The devices are characterised by an especially large coverage range of up to 100 metres under good free field conditions. All ENAIKOON remote-surveillance modules are compatible with the receiver of the ENAIKOON radio-switch-pro.

Each ENAIKOON radio-switch-pro is individually encoded. With more than 70 million code possibilities, it is 100% certain that your code is really unique.

Each receiver can accommodate an unlimited number of ENAIKOON radio-switch-pro handheld transmitters.

#### Technical Data of the Transmitter

Encoding:	Programmed with over 70 million code possibilities, user-coding also possible
Frequency:	433.92 MHz, 868.30 MHz (alternatively)
Channels:	Button 1: activate theft protection Button 2: de-activate theft protection Button 3: set off alarm
Modulation:	ASK
Coverage:	In good free field conditions up to 100 m (109 yd) possible
Power Supply:	1 x 3 V battery, CR 2032
Operation Control:	Light emitting diode (LED)
Temperature Range:	-20 °C to +60 °C (-4 °F to +140 °F)
Dimensions:	70 x 40 x 17 mm (2.76 x 1.58 x 0.67 in)
Weight:	ca. 25 g (0.88 oz.) (including batteries)

#### Technical Data of the Receiver

Power Supply:	12 V to 24 V AC/DC
Max. Current Consumption:	ca. 50 mA
Closed Current:	ca. 16 mA
Output Load:	60 V DC / 1 A / 30 W 125 V AC / 1 A / 62 VA
Temperature Range:	-20 °C to +60 °C (-4 °F to +140 °F)

## Products and Prices

Product	Part No.	Product Description	Price
ENAIKOON radio-switch pro	ZUB-04-01	Transmitter and receiver to control an ENAIKOON remote surveillance module	98 €
ENAIKOON transmitter pro	ZUB-04-02	Additional handheld transmitter for ENAIKOON radio-switch-pro, an unlimited number of transmitters can be used	49 €